

FEATURES & BENEFITS



cable ties for high temperature applications up to 115°C



for indoor use

MECHANICAL DATA

Material	poliamid 6.6
Halogen-free	yes
Colour	light green
Operating temperature [°C]	-40 ÷ +115
Minimum installation temperature [°C]	0

CERTIFICATES & STANDARDS


Flammability class	UL 94 V2
Standards	EN IEC 62275:2019

NOTE!




CE


Type	Index Ergom	Tensile strength, min. [daN]	Max. bundle dia. [mm]	Tool type	L	W
TKS2 9/3 (100 PCS)	E01TK-01090200101	8	20	MK III A, MK III PR	100	2,5
TKS2 12/3 (100 PCS)	E01TK-01090200201	8	27	MK III A, MK III PR	120	2,5
TKS2 16/3 (100 PCS)	E01TK-01090200301	8	39	MK III A, MK III PR	160	2,5
TKS2 20/3 (100 PCS)	E01TK-01090200401	8	52	MK III A, MK III PR	200	2,5
TKS2 14/3,6 (100 PCS)	E01TK-01090201101	18	33	MK III A, MK III B, MK III C, MK III PR	140	3,6
TKS2 20/3,6 (100 PCS)	E01TK-01090201201	18	46	MK III A, MK III B, MK III C, MK III PR	200	3,6
TKS2 30/3,6 (100 PCS)	E01TK-01090201301	18	84	MK III A, MK III B, MK III C, MK III PR	300	3,6
TKS2 20/5 (100 PCS)	E01TK-01090202101	22	50	MK III A, MK III B, MK III C, MK III PR	200	4,8
TKS2 30/5 (100 PCS)	E01TK-01090202201	22	81	MK III A, MK III B, MK III C, MK III PR	300	4,8
TKS2 40/5 (100 PCS)	E01TK-01090202301	22	103	MK III A, MK III B, MK III C, MK III PR	370	4,8
TKS2 30/8 (100 PCS)	E01TK-01090203101	54	82	MK III B, MK III C	300	7,6
TKS2 40/8 (100 PCS)	E01TK-01090203201	54	108	MK III B, MK III C	380	7,6
TKS2 50/8 (100 PCS)	E01TK-01090203301	54	162	MK III B, MK III C	550	7,6



1.1 - Ręczne zaciąganie opasek kablowych - włożyć końcówkę opaski kablowej w jej zamek



1.2 - Zaciągnąć ręcznie opaskę aż do pożądanego opasania przewodów



1.3 - Unikać przeginięcia opaski, nie poprawi to siły mocowania a może uszkodzić opaskę



1.4 - Odciąć wystającą część opaski za pomocą szczypiec, zostawiając kilka mm jako zabezpieczenie



2.1 - Zaciąganie opasek kablowych za pomocą narzędzia - ustawić maksymalną siłę napinania opaski przez narzędzie w zależności od rozmiaru opaski



2.2 - Chwycić opaskę kablową narzędziem